

# G-PL Series

## Ballast Compatible LED PL Base Lamps

### SPECIFICATION FEATURES & BENEFITS

- ▶ High efficiency retrofit for PL base CFL lamps in residential, commercial and industrial downlight applications.
- ▶ Compatibility with both electronic and magnetic ballast types.
- ▶ Fast and simple retrofit without changing existing ballasts or wiring.
- ▶ Line voltage 120VAC wiring option for maximum retrofit flexibility.
- ▶ Economical pricing for faster ROI in retrofit projects of all types.



### TECHNICAL SPECIFICATIONS

Model:	G-PL-E-C2-10	G-PL-E-C2-12	G-PL-M-C2-9	G-PL-M-C2-12
Wattage:	10W	12W	9W	12W
Base:	G24Q	G24Q	GX23	G24D
Lumens (2700K - 6000K):	800lm	1100lm	800lm	1100lm
Ballast Compatibility:	13W Electronic	18W Electronic	32W - 42W Magnetic / 120VAC Line Voltage	26W - 42W Magnetic / 120VAC Line Voltage
Voltage:	120VAC			
CCT Option:	3000K / 3500K / 4000K / 5000K			
Beam Angle:	300°			
CRI:	≥80			
Warranty:	25,000hrs.			

Notes: Luminous flux ±5% / CCT ±10% / CRI ±5% All values are nominal

### PART NUMBER SPECIFICATION

Series	Wattage	CCT Option
G-PL-E-C2 (Electronic Ballast Compatible)	10 (10 Watt) 12 (12 Watt)	30 (3000K) 35 (3500K)
G-PL-M-C2 (Magnetic Ballast / 120VAC Line Voltage Compatible)	9 (9 Watt) 12 (12 Watt)	40 (4000K) 50 (5000K)